

# DLD-2 Directional Logic Device

## A New Plug and Play "Micro" Device



### Features

- Adds yet another new dimension of simplicity to the industry.
- It's simple! No switches to set, no buttons to push, no questions to ask. Just connect it up and watch it work.
- Specifically designed to handle parking, drive-through and access control applications.
- Operates on any voltage from 10 to 30 Volts AC or DC.

### Overview

This directional logic device supplies the direction that a vehicle is going by using two detectors connected to two loops. Using this approach, one simply connects the relay outputs from the two vehicle detectors to this device's inputs and this unit takes it from there. It carefully measures the inputs and determines the direction the vehicle is moving: (1) from A to B or (2) from B to A, and indicates the direction by energizing the appropriate relay.

### Power

10 to 30 volts AC or DC, 3 mA typical

### Green Indicator

This green LED is the power indicator.

### Directional Indicator

This LED is a bi-color LED. When the A loop is entered first, the LED will blink with a green indication until the B loop is entered. It then turns a solid green. If the B loop is entered first, then the LED will blink with a red indication until the A loop is entered. It then turns a solid red. When the loops are both cleared, this LED will be dark.

### Inputs

There is one input for each direction. A normally open relay contact from the A detector is connected to Pin 3 and to Pin 2. A normally open relay contact from the B detector is connected to Pin 4 and to Pin 2.

### Outputs

There is one output for each direction: A to B on pin 5 and B to A on pin 6. When the directional indicator goes solid on, the appropriate relay will output a 300 ms pulse. No further outputs will be given until both loops are completely cleared.

### Size

Height: 1.52" Width: 2.9" Depth: 1.56"

### Connector

Removable 7-position terminal block

Pin assignments

- 1 – Power in (10 to 30 volts AC or +DC)
- 2 – Power common and inputs A & B common
- 3 – Detector A Input
- 4 – Detector B Input
- 5 – Relay for A to B (N.O. closes for directional indication)
- 6 – Relay for B to A (N.O. closes for directional indication)
- 7 – Output relay common



Proudly Made in the USA  
Veteran Owned & Operated

Diablo Controls, Inc.  
565 Dakota St, Unit F  
Crystal Lake, IL 60012

Toll Free 866-395-6677  
[www.diablocontrols.com](http://www.diablocontrols.com)



*Pros Who Know Trust Diablo*